

7-200 Home Theater Amplifier

The Sherbourn name is synonymous with innovation, performance and value. Its original amplifier was a single chassis, housing five mono blocks, five transformers and five heat-sinks. That design concept made for a smooth transition to the awesome 7-200, with seven of everything instead of five. Its massive 2.1kW, 4 ohm output requires 28 amps. To avoid the need for a special 30 amp circuit, Sherbourn includes two power cords for two 15 amp outlets.

Don't be content with an ordinary receiver. For little more money you can get Sherbourn's high-end home theater components and really enjoy the power and majesty of a movie soundtrack, the articulation of the human voice, the delicacy of a string quartet—everything is there on all Sherbourn products, thanks to a dedication to innovation, accuracy and performance.



7-200 Front



7-200 Inside



7-200 Rear

SPECIFICATIONS: 7-200 Home Theater Amplifier

Carton weight	115 lbs.
Rated power	200 watts per channel @ 8 ohms and 300 watts per channel @ 4 ohms with no more than 0.05% THD from 20 Hz-20 KHz all channels driven
Power bandwidth	5Hz-75KHz
Gain	30dB
Signal to noise ratio	110 dB/wide band, 110 dB/ A weighted
Input impedance	40 K ohms
Sensitivity	1.1 volts
Dynamic headroom	1.3 dB
Power supply	120v/60Hz or 230v/50Hz
Dimensions	17.7" W x 18.2" D x 7" H

SHERBOURN TECHNOLOGIES, INC.
19-3A Sterling Road
North Billerica, MA 01862 USA
Tel 978.663.7385 Fax 978.663.7389
www.Sherbourn.com

HOME
THEATER